

## Headset for Yealink SIP-T28 series



YHS32



SIP-T28P

### FEATURES

Ultra microphone noise cancelling, Quick disconnection support  
330 rotatable microphone boom.

Ultra light weight(only 50g) and comfortable wearing

Strong design, the life of boom rolling even to 30,000 times

Over-the-head style Pliable steel headband, ultra flex design

Large size ear pad, padded T-bar

ActiveProtection safeguards the user from acoustic burst

1x RJ9 headset jack, 1 meter cord line, Quick-disconnect(QD) cord

Transmit Sensitivity: -38.0 dB re. 1 V/Pa







Receiver Sensitivity: 95dB SPL +/-3 dB SPL

Receiver Impedance: 150

Voltage range: 1.0 - 10 V

Net weight: 50g

Accessories: leatherette ear cushion, foam ear cushion,  
adjustable clothing clip, headset hanger

Figure	Description
	<p>The headset is equipped with a quick disconnect. Users can connect the headset to a special adapter to connect to your IP phone.</p>
	<p>The headset are fitted with a standard modular connector. To use the headset models, simply insert the modular connector into the headset port of a compatible telephone.</p>
	<p>To adjust the headband, lengthen or shorten the adjustment rod until it fits comfortably. The click-stop feature keeps the headband securely adjusted. Position the headset receivers so that the foam cushions sit</p>
	<p>comfortably over the centre of your ears. On models with only one receiver, position the T-bar above your ear.</p>
	<p>Hold the receiver securely against your ear with one hand. With the other hand, Use the fixed boom, adjust the microphone to about one</p>
	<p>finger distance to your lips. The clothing clip helps to keep the headset properly positioned and free from the cord's weight. Attach the clothing clip at a comfortable level to liberate your hand.</p>

The Yealink YHS32 is compatible with all of the Yealink Enterprise IP phones. We will take the SIP-T28P for an example to make a brief description.

	<p>1</p> <p>2</p> <p>3</p> <p>4</p> <p>5</p> <p>6</p> <p>7</p> <p>8</p> <p>9</p> <p>10</p> <p>11</p>	<p>T-Bar (limited to one receiver products)</p> <p>Adjustable Headband</p> <p>Adjustment rod</p> <p>Ear cushion</p> <p>Click-Stop Turret</p> <p>Boom</p> <p>Microphone</p> <p>Headset Cable</p> <p>Clothing Clip</p> <p>Quick disconnectors</p> <p>J9 Modular Connector</p>
--	--	---

### Usage:

1. When there is an incoming call to your extension, press the HEADSET button to answer it by the headset mode.
2. During a conversation, press the HEADSET button or pickup the handset, the conversation will switch between the headset mode and the handset mode.